

# DC Power Supply and Battery Charger ELK-P112

**LIFETIME  
WARRANTY**

The ELK-P112 is a high quality Power Supply with a plug-in transformer and metal can enclosure. The P112 produces 12VDC @ 1 Amp. It features automatic resetting “fuseless” overload protection and diagnostic LED indicators. They are ideal for alarm, access control, and CCTV applications. Can be ordered with rechargeable battery by adding the “K” suffix. The P112K includes a 12V 5Ah battery.

## FEATURES

- Built-In Battery Charging Circuit
- Auto Reset “fuseless” Overload Protection (PTC)
- Visual AC and DC Power Indicators
- AC and DC Surge Suppression
- Lifetime Limited Warranty  
(2 Year Warranty on Battery)

## SPECIFICATIONS

- Regulated Output Voltage: 13.8 VDC
- Continuous Current Rating: 1 Amp
- Included Transformer: 16.5 V 45 VA
- Dimensions: 12”H x 12”W x 3.5”D
- Battery Recharging Capacity: 1.2Ah to 10 Ah

\*\* Higher output current (up to 2.5 Amps) may be drawn for a short time provided a fully charged battery is connected.



**Kit with 5Ah Battery  
ELK-P112K**



*Solutions for Serious Security and Automation Professionals*

(800) 797-9355 | [www.elkproducts.com](http://www.elkproducts.com)